


### **Output Ratings**

Voltage, Frequency		Prime	Standby
	kVA	45	50
	kW	45	50
	kVA		
	kW		

Ratings at 1 power factor.

Please refer to the output ratings technical data section for specific generator set outputs per voltage.





Dimensions and Weights						
Length	mm	1680 (66.1)				
Width	mm	760 (29.9)				
Height	mm	1330 (52.4)				
Weight (Dry)	kg	864 (1905)				
Weight (Wet)	kg	887 (1955)				

Ratings in accordance with ISO 8528, ISO 3046, IEC 60034, BS5000 and NEMA MG-1.22. Generator set pictured may include optional accessories.

#### Prime Rating

These ratings are applicable for supplying continuous electrical power (at variable load) in lieu of commercially purchased power. There is no limitation to the annual hours of operation and this model can supply 10% overload power for 1 hour in 12 hours.

#### **Standby Rating**

These ratings are applicable for supplying continuous electrical power (at variable load) in the event of a utility power failure. No overload is permitted on these ratings. The alternator on this model is peak continuous rated (as defined in ISO 8528-3).

#### Standard Reference Conditions

Note: Standard reference conditions 25°C (77°F) Air Inlet Temp, 100m (328 ft) A.S.L. 30% relative humidity. Fuel consumption data at full load with diesel fuel with specific gravity of 0.85 and conforming to BS2869: 1998, Class A2.

PEGC Power Solutions offer a range of optional features to allow you to tailor our generator sets to meet your power needs.Options available include:

- Upgrade to CE Certification
- A wide range of Sound Attenuated Enclosures
- A variety of generator set control and synchronising panels
- Additional alarms and shutdowns
- · A selection of exhaust silencer noise levels

For further information on all of the standard and optional features accompanying this product please contact your local Dealer or visit:

www.pegcpowersolutions.com



<b>Ratings and Perform</b>	ance Data				
Engine Make		Perkins			
Engine Model:		1103A-33TG2			
Alternator Make					
Alternator Model:		30030-M			
Control Panel:		100			
Base Frame:		Heavy Duty Fabricated Steel			
Circuit Breaker Type:	Circuit Breaker Type:		3 Pole MCCB		
Frequency:		50 HZ	60 HZ		
Engine Speed: RPM	rpm	1500	1800		
Fuel Tank Capacity:	litres (US gal)	145 (38.3)			
Fuel Consumption Prime	litres (US gal)/hr	12.6 (3.3)			
Fuel Consumption Standby	litres (US gal)/hr	14.1 (3.7)			
Engine Technical Dat	a				
		2			

Gross Engine Power St BMEP Prime	tandby kW (hp) kPa (psi)	60.5 (81) 1333 (193.4)	71.3 (96) 1279 (185.5)		
Gross Engine Power Pr		55 (74)	63.3 (85)		
Engine Speed	rpm	1500	1800		
Engine Perform	ance Data	50 Hz	60 Hz		
	( <sup>12</sup> )	\ - /			
Engine Weight Wet	kg (lb)	348 (767)			
Engine Weight Dry	, kg (lb)	341 (752)			
Battery Charger Amps		65			
Ground		Negative			
Voltage		12			
Moment of Inertia:	kg m <sup>2</sup> (lb/in <sup>2</sup> )	1.14 (3896)			
Displacement	L (cu. in)	3.3 (201.4)			
Compression Ratio		17.25:1			
Governing Class		ISO 8528 G2			
Governing Type		MECHANICAL			
Cooling Method		WATER			
Induction	()	TURBOCHARGED			
Stroke	mm (in)	127 (5)			
Bore	mm (in)	105 (4.1)			
Cycle		4 STROKE			
No. of Cylinders Alignment		IN LINE			



Fuel System						
Fuel Filter Type:				Replaceable E	lement	
Recommended Fuel:				Class A2 Diese	el	
Fuel Consumption at			110 % Load	100 % Load	75 % Load	50 % Load
50 Hz Prime:	l/hr (US gal/hr	)	14.1 (3.7)	12.6 (3.3)	9.6 (2.5)	6.9 (1.8)
50 Hz Standby	l/hr (US gal/hr	)	÷	14.1 (3.7)	10.6 (2.8)	7.4 (2)
60 Hz Prime	l/hr (US gal/hr	)				
60 Hz Standby	l/hr (US gal/hr	)	-			
(Based on diesel fuel with	a specific gravity of 0	.84 and conforming	to BS2869 classA	A2,EN590		
Air System				50 Hz	60 Hz	
Air Filter Type:					Replaceable Element	t
Combustion Air Flow Pr	ime	m³/min (cfm)	3	3.8 (134)		
Combustion Air Flow St	andby	m³/min (cfm)	3	3.9 (138)		
Max. Combustion Air Int	ake Restriction	kPa	8	3 (32.1)		
Cooling System				50 Hz	60 Hz	
Cooling System Capacit	y	l (US gal)	1	10.2 (2.7)		
Water Pump Type:					Centrifugal	
Heat Rejected to Water	& Lube Oil: Prime	kW (Btu/min)	3	35.2 (2002)		
Heat Rejected to Water	& Lube Oil: Standby	/ kW (Btu/min)	3	37.7 (2144)		
Heat Radiation to Room	*: Prime	kW (Btu/min)	1	14.3 (813)		
Heat Radiation to Room	n*: Standby	kW (Btu/min)	1	15.8 (899)		
Radiator Fan Load:		kW (hp)	1	l (1.3)		
Radiator Cooling Airflow	v:	m <sup>3</sup> /min (cfm)	1	110.4 (3899)		
External Restriction to C	ooling Airflow:	Pa (in H2O)	1	120 (0.5)		
*: Heat radiated from engir Designed to operate in aml Contact your local PEGC Pc conditions.	bient conditions up to ower Solutions Dealer 1		specific site			
Lubrication Syst	em					
Oil Filter Type:					Spin-On, Full Flow	
Total Oil Capacity:	l (US gal)				8.3 (2.2)	
Oil Pan Capacity:	l (US gal)				7.8 (2.1)	
Oil Type:					API CG4 / CH4 15W	-40
Oil Cooling Method:					WATER	
Exhaust System				50 Hz	60 Hz	
Maximum Allowable Bac	ck Pressure: kPa	(in Hg)	1	10 (3)		
Exhaust Gas Flow: Prime	e m <sup>3</sup>	/min (cfm)	1	10.1 (357)		
Exhaust Gas Flow: Stand	dby m <sup>3</sup>	/min (cfm)	1	10.4 (367)		
Exhaust Gas Temperatur	e: Prime °C (	°F)	5	557 (1035)		
Exhaust Gas Temperatur	re: Standby °C (	°F)	5	571 (1060)		



<b>Alternator Physical</b>	Data					
No. of Bearings:					1	
Insulation Class:					Н	
Winding Pitch:					2/3	
Winding Code					Μ	
Wires:					3	
Ingress Protection Rating:					IP23	
Excitation System:					SHUNT	
AVR Model:					R121	
dependant on voltage code selected	d					
<b>Alternator Operatin</b>	ig Data					
Overspeed: rpm					2250	
Voltage Regulation: (Steady	state)	%			+/- 1.0	
Wave Form NEMA = TIF:					100	
Wave Form IEC = THF:		%			2	
Total Harmonic content LL/L	_N:	%			3.5	
Radio Interference:					EN61000-6	
Radiant Heat: 50 Hz		kW (Btu/min)			4.8 (273)	
Radiant Heat: 50 Hz		kW (Btu/min)				
Radiant Heat: 50 Hz Radiant Heat: 60 Hz		kW (Btu/min) kW (Btu/min)			0 ()	
	ance Da	kW (Btu/min)	240 V	230 V		
Radiant Heat: 60 Hz Alternator Performa Voltage Code		kW (Btu/min)			0 () 220 V	
Radiant Heat: 60 Hz Alternator Performa Voltage Code Motor Starting Capability*	kVA	kW (Btu/min)	145	136	0 () 220 V 128	270
Radiant Heat: 60 Hz Alternator Performa Voltage Code Motor Starting Capability* Short Circuit Capacity**	kVA %	kW (Btu/min)	145 270	136 270	0 () 220 V 128 270	270
Radiant Heat: 60 Hz Alternator Performa Voltage Code Motor Starting Capability*	kVA % Xd	kW (Btu/min)	145 270 1.443	136 270 1.571	0 () 220 V 128 270 1.717	270
Radiant Heat: 60 Hz Alternator Performa Voltage Code Motor Starting Capability* Short Circuit Capacity**	kVA % Xd X'd	kW (Btu/min)	145 270 1.443 0.121	136 270 1.571 0.132	0 () 220 V 128 270 1.717 0.145	270
Radiant Heat: 60 Hz Alternator Performa Voltage Code Motor Starting Capability* Short Circuit Capacity**	kVA % Xd	kW (Btu/min)	145 270 1.443	136 270 1.571	0 () 220 V 128 270 1.717	270
Radiant Heat: 60 Hz Alternator Performa Voltage Code Motor Starting Capability* Short Circuit Capacity**	kVA % Xd X'd X"d	kW (Btu/min) ita 50 Hz:	145 270 1.443 0.121	136 270 1.571 0.132	0 () 220 V 128 270 1.717 0.145	270
Radiant Heat: 60 Hz Alternator Performa Voltage Code Motor Starting Capability* Short Circuit Capacity** Reactances	kVA % Xd X'd X"d	kW (Btu/min) ita 50 Hz:	145 270 1.443 0.121	136 270 1.571 0.132	0 () 220 V 128 270 1.717 0.145	270
Radiant Heat: 60 Hz Alternator Performa Voltage Code Motor Starting Capability* Short Circuit Capacity** Reactances Alternator Performa Voltage Code	kVA % Xd X'd X"d	kW (Btu/min) ita 50 Hz:	145 270 1.443 0.121	136 270 1.571 0.132	0 () 220 V 128 270 1.717 0.145	270
Radiant Heat: 60 Hz Alternator Performa Voltage Code Motor Starting Capability* Short Circuit Capacity** Reactances Alternator Performa Voltage Code Motor Starting Capability*	kVA % Xd X'd X''d <b>Ance Da</b>	kW (Btu/min) ita 50 Hz:	145 270 1.443 0.121 0.079	136 270 1.571 0.132 0.079	0 () 220 V 128 270 1.717 0.145 0.087	270
Radiant Heat: 60 Hz Alternator Performa Voltage Code Motor Starting Capability* Short Circuit Capacity** Reactances Alternator Performa	kVA % X'd X'd X''d <b>ance Da</b>	kW (Btu/min) Ita 50 Hz:	145 270 1.443 0.121 0.079	136 270 1.571 0.132 0.079	0 () 220 V 128 270 1.717 0.145 0.087	
Radiant Heat: 60 Hz          Alternator Performation         Voltage Code         Motor Starting Capability*         Short Circuit Capacity**         Reactances         Alternator Performation         Voltage Code         Motor Starting Capability*         Short Circuit Capacity**         Reactances         Alternator Performation         Voltage Code         Motor Starting Capability*         Short Circuit Capacity**	kVA % Xd X'd X"d Ance Da	kW (Btu/min) Ita 50 Hz:	145 270 1.443 0.121 0.079	136 270 1.571 0.132 0.079	0 () 220 V 128 270 1.717 0.145 0.087	

Reactances shown are applicable to prime ratings.

\*Based on 30% voltage dip at 0.9 power factor.

\*\* With optional independant excitation system (PMG / AUX winding)



Output Ratings 50 Hz						
	Prime			Standby		
Voltage Code	kVA	kW	kVA	kW		
415/240V						
400/230V						
380/220V						
230/115V						
220/127V						
220/110V						
200/115V						
240V	45	45	50	50		
230V	45	45	50	50		
220V	45	45	50	50		

### Output Ratings 60 Hz

	Prime			Standby	
Voltage Code	kVA	kW	kVA	kW	
480/277V					
440/254V					
416/240V					
400/230V					
380/220V					
240/139V					
240/120V					
230/115V					
220/127V					
220/110V					
208/120V					
240/120					
220/110					





### **Dealer Contact Details**

### Documentation

Operation and maintenance manual including circuit wiring diagrams.

#### **Generator Set Standards**

The equipment meets the following standards: BS5000, ISO 8528, ISO 3046, IEC 60034, NEMA MG-1.22.

### Warranty

6.8 - 750 kVA electric power generation products in prime applications the warranty period is 12 months from date of start-up, unlimited hours (8760). For standby applications the warranty period is 24 months from date of start-up, limited to 500 hours per year.

730 - 2500 kVA electric power generation products in prime applications the warranty period is 12 months from date of start-up, unlimited hours (8760 hours) or 24 months from date of start-up, limited to 6000 hours. For standby applications the warranty period is 36 months from date of start-up, limited to 500 hours per year.

PEGC Power Solutions manufactures product in the following locations:

Lahore Karachi Islamabad Multan With headquarters in Lahore, PEGC Power Solutions operates through a Global Dealer

Network. To contact your local Sales Office please visit the PEGC Power Solutions website at www.pegcpowersolutions.com.

PEGC Power Solutions is a trading name of Public Electric Generator Concern (PEGC Power Solutions & Engineering Services (Pvt) Ltd.).

In line with our policy of continuous product development, we reserve the right to change specification without notice.