


P9.5-1 (Skid)

Output Ratings				
Voltage, Frequency	Prime	Standby		
kVA	8.5	9.5		
kW	6.8	7.6		
kVA				
kW				



Ratings at 1 power factor.

Please refer to the output ratings technical data section for specific generator set outputs per voltage.



Dimensions and Weights					
Length	mm	1550 (61)			
Width	mm	620 (24.4)			
Height	mm	1020 (40.2)			
Weight (Dry)	kg	233 (514)			
Weight (Wet)	kg	238 (525)			

Ratings in accordance with ISO 8528, ISO 3046, IEC 60034, BS5000 and NEMA MG-1.22.

Generator set pictured may include optional accessories.

Prime Rating

These ratings are applicable for supplying continuous electrical power (at variable load) in lieu of commercially purchased power. There is no limitation to the annual hours of operation and this model can supply 10% overload power for 1 hour in 12 hours.

Standby Rating

These ratings are applicable for supplying continuous electrical power (at variable load) in the event of a utility power failure. No overload is permitted on these ratings. The alternator on this model is peaking continuous rated (as defined in ISO 8528-3).

Standard Reference Conditions

Note: Standard reference conditions 25°C (77°F) Air Inlet Temp, 100m (328 ft) A.S.L. 30% relative humidity. Fuel consumption data at full load with diesel fuel with specific gravity of 0.85 and conforming to BS2869: 1998, Class A2.

PEGC Power Solutions offer a range of optional features to allow you to tailor our generator sets to meet your power needs. Options available include:

- Upgrade to CE Certification
- A wide range of Sound Attenuated Enclosures
- A variety of generator set control and synchronizing panels
- Additional alarms and shutdowns
- A selection of exhaust silencer noise levels

For further information on all of the standard and optional features accompanying this product please contact your local Dealer or visit:



Ratings and Perform	ance Data					
Engine Make		Perkins				
Engine Model:		403A-11G1				
Alternator Make						
Alternator Model:		10030				
Control Panel:		100				
Base Frame:		Heavy Duty Fabricated Steel				
Circuit Breaker Type:						
Frequency:		50 HZ	60 HZ			
Engine Speed: RPM	rpm	1500				
Fuel Tank Capacity:	litres (US gal)					
Fuel Consumption Prime	litres (US gal)/hr	2.5 (0.7)				
Fuel Consumption Standby	litres (US gal)/hr	2.8 (0.7)				
Engine Technical Dat	a					
No. of Cylinders		3				
Alignment		IN LINE				
Cycle		4 STROKE				
Bore mr	n (in)	77 (3)				
Stroke mr	n (in)	81 (3.2)				
Induction		NATURALLY ASPIRATED				
Cooling Method		WATER				
Governing Type		MECHANICAL				
Governing Class		ISO 8528				
Compression Ratio		23:1				
Displacement L (cu. in)	1.1 (69)				
Moment of Inertia: kg	m² (lb/in²)	1.63 (5570)				
Voltage		12				
Ground		Negative				
Battery Charger Amps		15				
Engine Weight Dry kg	(lb)	129 (284)				
Engine Weight Wet kg	(lb)	139 (306)				
Funta - Pu 6	Data	F0.11-				
Engine Performance		50 Hz	60 Hz			
Engine Speed	rpm	1500				
Gross Engine Power Prime	kW (hp)	8.6 (12)				
Gross Engine Power Standby	kW (hp)	9.5 (13)				
BMEP Prime	kPa (psi)	610 (88.5)				
BMEP Standby	kPa (psi)	672 (97.4)				



Fuel System						
Fuel Filter Type:			Replaceable Ele	ment		
Recommended Fuel:				Class A2 Diesel		
Fuel Consumption at			110 % Load	100 % Load	75 % Load	50 % Load
50 Hz Prime:	l/hr (US gal	/hr)	2.8 (0.7)	2.5 (0.7)	1.9 (0.5)	1.5 (0.4)
50 Hz Standby	l/hr (US gal	/hr)	-	2.8 (0.7)	2.1 (0.6)	1.6 (0.4)
60 Hz Prime	l/hr (US gal	/hr)				
60 Hz Standby	l/hr (US gal	/hr)	-			
(Based on diesel fuel with	h a specific gravity o	f 0.84 and conforming t	to BS2869, class A2			
Air System			50 H	<u> </u>	60 Hz	
Air Filter Type:					Replaceable Elemen	t
Combustion Air Flow I	Prime	m³/min (cfm)	0.7 (25)			
Combustion Air Flow	Standby	m³/min (cfm)	0.7 (25))		
Max. Combustion Air I	ntake Restriction	kPa	6.4 (25.	7)		
Cooling System]		50 H		60 Hz	
Cooling System Capac		l (US gal)	5.2 (1.4			
Water Pump Type:	. ,	(00 5)	·	<u>, </u>	Centrifugal	
Heat Rejected to Wate	r & Lube Oil: Prime	kW (Btu/min)	8.3 (47)	2)		
Heat Rejected to Wate			9.5 (54)	0)		
Heat Radiation to Room		kW (Btu/min)	2.9 (16	5)		
Heat Radiation to Roo	m*: Standby	kW (Btu/min)	3.9 (22)			
Radiator Fan Load:		kW (hp)	0.2 (0.3)		
Radiator Cooling Airfle	ow:	m³/min (cfm)	24 (848	3)		
External Restriction to	Cooling Airflow:	Pa (in H2O)	125 (0.	5)		
*: Heat radiated from eng Designed to operate in a Contact your local PEGC conditions.	mbient conditions up		specific site			
Lubrication Sys	tem					
Oil Filter Type:					Spin-On, Full Flow	
Total Oil Capacity:	l (US gal)				4.9 (1.3)	
Oil Pan Capacity:	l (US gal)				4.4 (1.2)	
Oil Type:					API CH4 15W-40	
Oil Cooling Method:					N/A	
Exhaust System			50 H	Z	60 Hz	
Maximum Allowable B	ack Pressure:	(Pa (in Hg)	10.2 (3)		
Exhaust Gas Flow: Prin	ne r	m³/min (cfm)	1.7 (59			
Exhaust Gas Flow: Sta		m³/min (cfm)	1.8 (64)			
Exhaust Gas Temperati	ure: Prime	C (°F)	368 (69	94)		

420 (788)

°C (°F)

Exhaust Gas Temperature: Standby



Alternator Physical	Data						
No. of Bearings:					1		
Insulation Class:					Н		
Winding Pitch:					2/3		
Winding Code					6		
Wires:					12		
Ingress Protection Rating:					IP23		
Excitation System:					SHUNT		
AVR Model:					R121		
dependant on voltage code selected	d						
Alternator Operatin	g Data						
Overspeed: rpm					2250		
Voltage Regulation: (Steady	state)	%			+/- 0.5		
Wave Form NEMA = TIF:					50		
Wave Form IEC = THF:		%			2		
Total Harmonic content LL/L	_N:	%			3.5		
Radio Interference:					EN61000-6		
					1.5 (85)		
Radiant Heat: 50 Hz		kW (Btu/min)			()		
Radiant Heat: 60 Hz	ance Da	kW (Btu/min)					
	ance Da	kW (Btu/min)	415/240 V	400/230 V	380/220 V		
Radiant Heat: 60 Hz Alternator Performa Voltage Code		kW (Btu/min)			380/220 V	21	
Alternator Performation Voltage Code Motor Starting Capability*	kVA	kW (Btu/min)	415/240 V 18	400/230 V 17 0			
Radiant Heat: 60 Hz Alternator Performa Voltage Code Motor Starting Capability* Short Circuit Capacity**	kVA %	kW (Btu/min)	18 0	17 0	380/220 V 16 0	21 0	
Alternator Performation Voltage Code Motor Starting Capability*	kVA % Xd	kW (Btu/min)	18 0 1.323	17 0 1.424	380/220 V 16 0 1.578		
Radiant Heat: 60 Hz Alternator Performa Voltage Code Motor Starting Capability* Short Circuit Capacity**	kVA %	kW (Btu/min)	18 0	17 0	380/220 V 16 0		
Alternator Performa Voltage Code Motor Starting Capability* Short Circuit Capacity** Reactances Alternator Performa	kVA % Xd X'd X"d	kW (Btu/min)	18 0 1.323 0.21	17 0 1.424 0.23	380/220 V 16 0 1.578 0.25		
Radiant Heat: 60 Hz Alternator Performa Voltage Code Motor Starting Capability* Short Circuit Capacity** Reactances	kVA % Xd X'd X"d	kW (Btu/min)	18 0 1.323 0.21	17 0 1.424 0.23	380/220 V 16 0 1.578 0.25		
Alternator Performation Voltage Code Motor Starting Capability* Short Circuit Capacity** Reactances Alternator Performation Voltage Code Motor Starting Capability*	kVA % Xd X'd X"d	kW (Btu/min)	18 0 1.323 0.21	17 0 1.424 0.23	380/220 V 16 0 1.578 0.25		
Alternator Performa Voltage Code Motor Starting Capability* Short Circuit Capacity** Reactances Alternator Performa Voltage Code	kVA % Xd X'd X"d	kW (Btu/min)	18 0 1.323 0.21 0.073	17 0 1.424 0.23 0.073	380/220 V 16 0 1.578 0.25 0.081	0	
Alternator Performation Voltage Code Motor Starting Capability* Short Circuit Capacity** Reactances Alternator Performation Voltage Code Motor Starting Capability*	kVA % Xd X'd X"d	kW (Btu/min) Ita 50 Hz:	18 0 1.323 0.21 0.073	17 0 1.424 0.23 0.073	380/220 V 16 0 1.578 0.25 0.081	18	
Alternator Performation Voltage Code Motor Starting Capability* Short Circuit Capacity** Reactances Alternator Performation Voltage Code Motor Starting Capability* Short Circuit Capacity**	kVA % Xd X'd X"d X"d	kW (Btu/min) Ita 50 Hz:	18 0 1.323 0.21 0.073	17 0 1.424 0.23 0.073	380/220 V 16 0 1.578 0.25 0.081	18	

Reactances shown are applicable to prime ratings.

^{*}Based on 30% voltage dip at 0.9 power factor.

^{**} With optional independant excitation system (PMG / AUX winding)

P9.5-1 (Skid)

220/127V 220/110V

208/120V 240/120 220/110



Output Ratings	50 Hz				
		Prime		Standby	
Voltage Code	kVA	kW	kVA	kW	
415/240V	8.5	6.8	9.5	7.6	
400/230V	8.5	6.8	9.5	7.6	
380/220V	8.5	6.8	9.5	7.6	
230/115V					
220/127V					
220/110V					
200/115V					
240V					
230V					
220V					
Output Ratings	60 Hz				
		Prime		Standby	
Voltage Code	kVA	kW	kVA	kW	
480/277V					
440/254V					
416/240V					
400/230V					
380/220V					
400/230V 380/220V 240/139V 240/120V					





P9.5-1 (Skid)

Dealer Contact Details

Documentation

Operation and maintenance manual including circuit wiring diagrams.

Generator Set Standards

The equipment meets the following standards: BS5000, ISO 8528, ISO 3046, IEC 60034, NEMA MG-1.22.

Warranty

6.8 - 750 kVA electric power generation products in prime applications the warranty period is 12 months from date of start-up, unlimited hours (8760). For standby applications the warranty period is 24 months from date of start-up, limited to 500 hours per year.

730 - 2500 kVA electric power generation products in prime applications the warranty period is 12 months from date of start-up, unlimited hours (8760 hours) or 24 months from date of start-up, limited to 6000 hours. For standby applications the warranty period is 36 months from date of start-up, limited to 500 hours per year.

PEGC Power Solutions manufactures product in the following locations:

Lahore Karachi Islamabad Multan

With headquarters in Lahore, PEGC Power Solutions operates through a Global Dealer Network. To contact your local Sales Office please visit the PEGC Power Solutions website at www.pegcpowersolutions.com.

PEGC Power Solutions is a trading name of Public Electric Generator Concern (PEGC Power Solutions & Engineering Services (Pvt) Ltd.).

In line with our policy of continuous product development, we reserve the right to change specification without notice.